

Important

- An existing system backup for devices with firmware version up to 1.6.4 cannot be used to restore the system configuration for devices with firmware version 2.0.1 or higher!
- The entire device configuration (IP-side) must be completely restored manually after an upgrade.
- For this purpose, we recommend documenting the current configuration, e.g. by means of screenshots.
- Depending on the current configuration, the upgrade may take longer than a new commissioning.

For the firmware upgrade to version 2.0.1 the following is required:

- License file that matches the current license scope.
- XML file (In-Home bus) that matches the current system state.
- Complete documentation (e.g. IP users, telephony, etc.), of the current Smart Gateway configuration.

Update to firmware version 2.0.1:

For all Smart Gateway Professional (SG 650) with firmware versions below 1.3.x, the following sequence must be observed when updating to firmware version 2.0.1:

- Current firmware version = 1.0.0 or 1.1.0:

Step 1: Install the update to 1.2.1

Step 2: Install the update to 1.3.3

Step 3: Install the update to 2.0.1

- Current firmware version = 1.2:

Step 1: Install the update to 1.2.1

Step 2: Install the update to 1.3.3

Step 3: Install the update to 2.0.1

- Current firmware version = 1.2.1:

Step 1: Install the update to 1.3.3

Step 2: Install the update to 2.0.1